



# ONE SYSTEMS

## Bi-Amp Presets

### 208CIM

|                  | <b>LF</b>   | <b>HF</b>   |
|------------------|-------------|-------------|
| <b>Gain</b>      | 0 dB        | -6.0 dB     |
| <b>Polarity</b>  | Norm        | Norm        |
| <b>EQ1</b>       |             |             |
| <b>Type</b>      | PEQ         | PEQ         |
| <b>Level</b>     | -3.0 dB     | -4.5 dB     |
| <b>Frequency</b> | 1,000 Hz    | 1,224 Hz    |
| <b>Bandwidth</b> | 0.63 Octave | 0.33 Octave |
| <b>EQ2</b>       |             |             |
| <b>Type</b>      | PEQ         | PEQ         |
| <b>Level</b>     | -1.5 dB     | -4.5 dB     |
| <b>Frequency</b> | 793 Hz      | 3,084Hz     |
| <b>Bandwidth</b> | 0.3 Octave  | 0.53 Octave |
| <b>EQ3</b>       |             |             |
| <b>Type</b>      | PEQ         | PEQ         |
| <b>Level</b>     | +4.0 dB     | +8.0 Octave |
| <b>Frequency</b> | 80 Hz       | 12,000 Hz   |
| <b>Bandwidth</b> | 0.7 Octave  | 0.67 Octave |

## EQ4

|           |            |
|-----------|------------|
| Type      | PEQ        |
| Level     | -2.0 dB    |
| Frequency | 1,500 Hz   |
| Bandwidth | 0.3 Octave |

## Delay

|           |        |
|-----------|--------|
| 0.12 mSec | 0 mSec |
|-----------|--------|

## Crossover

|           |                      |
|-----------|----------------------|
| LPF       |                      |
| Frequency | 1,633 Hz             |
| Type      | 24 dB Linkwitz-Riley |

|           |                  |                         |
|-----------|------------------|-------------------------|
| HPF       |                  |                         |
| Frequency | 55 Hz            | 1,633 Hz                |
| Type      | Butterworth 24dB | 24 dB<br>Linkwitz-Riley |



